



COLOR i7

OPERATION MANUAL



CE Declaration

Manufacturer's Name:	X-Rite, Incorporated
Manufacturer's Address:	4300 44 th Street, S.E. Grand Rapids, Michigan U.S.A.
Model Name:	Color i7
Model No.:	CI7
Directive(s) Conformance:	EMC 89/336/EEC LVD 73/23/EEC

WEEE

As of August 13, 2005, X-Rite products meet the European Union – Waste Electrical and Electronic Equipment (WEEE) directive. Please refer to www.xrite.com for more information on X-Rite's compliance with the WEEE directive.



Federal Communications Commission Notice

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Industry Canada Compliance Statement

This Class A digital apparatus complies with Canadian ICES-003.
Cet appareil numérique de la classe A est conforme à la norme NMB-003 du Canada.

Equipment Information



Use of this equipment in a manner other than that specified by X-Rite, Incorporated may compromise design integrity and become unsafe.

Proprietary Notice

The information contained in this manual is derived from patent and proprietary data of X-Rite, Incorporated. The contents of this manual are the property of X-Rite, Incorporated and are copyrighted. Any reproduction in whole or part is strictly prohibited. Publication of this information does not imply any rights to reproduce or use this manual for any purpose other than installing, operating, or maintaining this instrument. No part of this manual may be reproduced, transcribed, transmitted, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, magnetic, mechanical, optical, manual, or otherwise, without the prior written permission of an officer of X-Rite, Incorporated.

This product may be covered by one or more patents. Refer to the instrument for actual patent numbers.

Copyright © 2007 by X-Rite, Incorporated
“ALL RIGHTS RESERVED”

Limited Warranty

X-Rite, Incorporated (“X-Rite”) warrants each instrument manufactured to be free of defects in material and workmanship for a period of 12 months. This warranty shall be fulfilled by the repair or replacement, at the option of X-Rite, of any part or parts, free of charge including labor, F.O.B. its factory or authorized service center.

This warranty shall be voided by any repair, alteration, or modification, by persons other than employees of X-Rite, or those expressly authorized by X-Rite to perform repairs, and by any abuse, misuse, or neglect of the product, or by use not in accordance with X-Rite’s published instructions.

X-Rite reserves the right to make changes in design and /or improvements to its products without any obligation to include these changes in any products previously manufactured. Correction of defects by repair or replacement shall constitute fulfillment of all warranty obligations on the part of X-Rite.

THIS WARRANTY IS EXPLICITLY IN LIEU OF ANY OTHER EXPRESSED OR IMPLIED WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. THIS WARRANTY OBLIGATION IS LIMITED TO REPAIR OR REPLACEMENT OF THE UNIT RETURNED TO X-RITE OR AN AUTHORIZED SERVICE CENTER FOR THAT PURPOSE.

This agreement shall be interpreted in accordance with the laws of the State of Michigan and jurisdiction and venue shall lie with the courts of Michigan as selected by X-Rite, Incorporated.

Table of Contents

Before using your spectrophotometer	2
Safety first!	2
Performance and Environmental Specifications	3
What's in the box?	4
Optional Accessories	5
Spectrophotometer Setup.....	6
Sample Preview Methods.....	6
<i>Sample Door</i>	7
<i>Computer Monitor Used for Sample Preview</i>	8
Operation.....	10
Status Panel	10
Calibration	11
Taking Reflectance Measurements.....	12
Taking Transmission Measurements	13
UV Control	15
Aperture Control.....	16
Specular Control	16
Maintaining Your Spectrophotometer	17
Cleaning the Calibration Tiles.....	17
Cleaning the Black Plastic Blocking Panel	17
Color Science Training	18
Technical Service.....	19
Spare Parts and Accessories	20

Welcome

Congratulations on your ownership of the Color i7 benchtop spectrophotometer. Your Color i7 is a reflectance / transmittance reference-level, dual beam sphere benchtop spectrophotometer offering agreement with these X-Rite / GretagMacbeth instruments: 7000A, Color i5, 2180UV, and CE-XTH. Your Color i7 Spectrophotometer offers these features:

- Multiple areas of view in both reflectance and transmittance.
- Self-adjusting, dual zoom lens that eliminates configuration errors between aperture plates and lens position.
- Computer monitor and hinged sample door video preview for measurement accuracy and targeting purposes.
- Haze Measurement mode.
- Automated ultra violet adjustment when measuring fluorescent or optically brightened samples.
- USB and RS-232 interfaces that eliminate connectivity issues.
- Clear status panel display with dual remote read buttons for standard and sample measurements and warning indicators for calibration interval.
- Dampened sample arm holder that prevents sample damage.
- Supports Embedded NetProfiler.

Before using your spectrophotometer...

- 1 Review the Safety First Recommendations, on page 2 to ensure a safe working environment.
- 2 Review the Environmental Specifications on page 3 to make sure you are using your spectrophotometer in an environmentally appropriate location.

Safety first!

Your Color i7 spectrophotometer is very safe to use. However, like all electronic equipment you must follow these common sense safety guidelines to ensure your personal safety and the future integrity of the unit.

- **PLEASE READ AND FOLLOW INSTRUCTIONS**— It will be helpful to you if you review this document completely before you attempt to install and use your Color i7.
- **RETAIN THIS MANUAL FOR FUTURE REFERENCE**—Keep this manual handy for others to read or refer to when they need to operate the unit.
- **OBEY WARNINGS**—Please follow all of the precautions described in this operation manual. If you use your spectrophotometer in a manner not intended, the built in safety protection may be impaired.
- **PROTECT FROM WATER AND MOISTURE**—Do not use your spectrophotometer in an area where there is a possible hazard of electric shock from spilled water or other liquids or uncontrolled moisture.
- **NOT FOR USE IN AN EXPLOSIVE ENVIRONMENT!**- Do not use your spectrophotometer in an area where there is the possibility of explosions.

Performance and Environmental Specifications

Performance Specifications	
Repeatability	0.01 RMS ΔE CIELAB White tile
Inter-Instrument Agreement	0.08 Avg. 13 BCRA Series II tiles SCI (LAV only)
Geometry	D/8 Tri-beam simultaneous SCE\SCI
Illumination	Pulsed Xenon, D65 Calibrated
Measurement time	2.7 – 4.0 seconds (flash & data acquisition)
Duty cycle	480 measurements per hour max
Spectral Range	360 to 750 nm
Wavelength Interval	10 nm
Photometric range	0.0% to 200%
Photometric resolution	0.001% reflectance

Environmental Specifications	
Electrical Requirements	100-240 VAC/50-60 Hz, UL Category II AC line input is 1.5 amps.
Operating Temperature Storage Temperature	10° C to 35° C -20° C to 55° C
Altitude	Maximum 2000M
Pollution	UL Category 2
Operating Humidity Storage Humidity	20% to 80% relative, non-condensing 05% to 90% relative, non-condensing
Dimensions	23 cm W x 25 cm H x 47 cm D
Weight	12 kgs
Interface	USB/RS-232/38400 baud

What's in the box?

If you are reading this documentation, you have already followed the instructions detailed in the Color i7 Installation Card found as the first item in the shipping box. You should always keep your installation card handy for reference. Keep your shipping box in case you need to return your unit to the factory for service. Here is a handy list of the contents of the shipping container when it arrived at your location:

- **Software box containing the Color i7 Driver and Documentation CD along with any other software you may have ordered such as Color iControl and NetProfiler.**
- **Color i7 Spectrophotometer with Large Area of View, 25 mm Reflectance Aperture plate installed**
- **12-volt power supply**
- **Round white calibration tile**
- **Round green performance tile**
- **Black trap for calibration**
- **Standards (tiles) cleaner & tissues**
- **17mm, 10mm, & 6mm aperture plates**
- **White Fluorescent standard in an envelope**
- **Warnings document (containing all of the caution statements in this document)**
- **Certificate of performance**
- **USB and RS-232 communications cables in a labeled cable bag**
- **The following power cords:**
 - **11.74.16 mains cord for Switzerland**
 - **11.74.17 mains cord for Germany**
 - **A-CB/D19US mains cord for the USA**

Optional Accessories

The following are *optional* items you may purchase for your Color i7. You may have already purchased some of these optional accessories. Please refer to Spare Parts and Accessories on page 20 for ordering information.

- Application software: found in the “Software” box, such as NetProfiler and Color iControl
- NetProfiler standards: if you ordered NetProfiler software
- Stand for Horizontal Measurement Plane
- Transmission kit (Accessory/transmission box):
 - Base Plate and Thumb screws (2)
 - Barium Coated Aperture Plate
 - Cuvette holder
 - Transmission cuvette
 - 22 mm sphere LAV stop and spring retainer mountable to the base
 - 17 mm sphere stop and spring retainer mountable to the base
 - 10 mm sphere MAV stop and spring retainer mountable to the base
 - 6 mm sphere SAV stop and spring retainer mountable to the base
 - Black Trap
 - Spectralon plaque assembly

Spectrophotometer Setup

Please follow the instructions detailed in the Color i7 Installation Card found as the first item in your shipping box when you opened it.



Sample Preview Methods

The Color i7 spectrophotometer has three possible sample preview methods:

Sample Door- this choice enables you to open the sample door and look at the sample position in the viewport and make manual adjustments if necessary to obtain optimum sample alignment. Go to page 7 for instructions on using the Sample Door Preview Method.

Computer Monitor Used for Sample Preview- This preview method involves installing an external video to USB adapter for using your computer monitor for sample preview. This method was installed when your instrument first arrived at your location and was part of the instructions detailed on the Color i7 installation card. Please refer to the instructions on this card.

LCD Sample Preview Monitor- This optional preview method involves installing a special, mini monitor that mounts on top of the Ci7. This choice presents a live picture of your sample at the view port and projects it onto the mini monitor mounted on top of the spectrophotometer. Go to page 8 for instructions on using the LCD Sample Preview Monitor Method.

Sample Door

The Color i7 sample door is capable of opening for a completely unobstructed view of the sample presented at the view port. When completely open, the sample door allows you to adjust the sample at the view port for optimal placement.

To use the Sample Door, proceed as follows:

1. Position your sample at the viewport.
2. Open the sample arm by grasping it and pulling it towards you. Place your sample at the view port and close the sample arm.
3. Using your fingertips, open the door at the pry notches and gently lower the door to the complete open position. See the figure below.




Figure 1. Opening the Hinged Sample Door

4. With the Sample Door completely open, view the sample at the view port and make sure the sample is in an optimal position for measuring.




Figure 2. Observing the Sample through the Viewport Opening

5. Close the Sample Door. Prepare for measurement.

Computer Monitor Used for Sample Preview

This preview option was installed at the time of instrument setup. To use the option press the **Preview** button on the spectrophotometer to view an image of the sample at the Ci7 viewport on your PC monitor. If you are using Color iControl software, make sure that you check the box: **ENABLE SENSOR READ BUTTON/PREVIEW SUPPORT** on the Spectrophotometer Installation Wizard screen to make sure this button is activated.

Optional LCD Sample Preview Monitor

An optional sample preview monitor is available to use with your spectrophotometer. Using a camera within the spectrophotometer, a live picture of your sample is taken at the view port. The camera then projects the live image onto the preview monitor. This is helpful since you can adjust your sample placement at the view port for targeting purposes using the monitor to guide your adjustment.

Installing the LCD Sample Preview Monitor

To install your preview monitor, proceed as follows. Refer to **Error! Reference source not found.** if needed.

1. Remove the screen from any shipping/packaging material. The preview monitor should have a cable attached with a four-prong female connector at one end. You should also locate the preview monitor spectrophotometer cable with a four-prong male connector at one end and two spectrophotometer connectors at the other end (one is yellow, the other is black).
2. Remove the Preview Monitor mounting screw cap and store it in a safe place. The mounting screw should now be exposed.




Figure 3. Preview Sample Monitor

COLOR 17 OPERATION MANUAL

3. Align the mounting screw hole on the monitor stem to the mounting screw fixed on the spectrophotometer. Rotate the entire monitor assembly around the fixed mounting screw on the spectrophotometer. Continue to rotate until the monitor is secure.
4. Use the adjustment knob on the monitor stem to pivot the monitor around the ball joint to adjust the angle of the monitor for your viewing needs.
5. Connect the four-pin connector on the monitor cable to the four-pin male connector on the monitor cable.
6. Connect the RCA Video connector on the monitor-spectrophotometer cable to the RCA connector at the rear of the spectrophotometer. Connect the black connector on the monitor spectrophotometer cable to the black connector at the rear of the spectrophotometer.
7. The monitor should be powered on and whatever sample is currently on the view port is seen on the display. If the monitor is not showing an image, press the power button on the side of the monitor to turn it on.

Operation

Status Panel




Figure 4. Color i7 Front Status Panel

Programmable Status Panel Buttons

Standard and **Trial** buttons are available but must be supported by your application software and function as programmed.

The **Sample Preview** button is used with the Computer Monitor Video Preview.

Calibration

Calibration is recommended every **8** hours of spectrophotometer operation. Each spectrophotometer configuration that is used should be calibrated. A configuration consists of four components:

1. Measurement Mode: Transmission, Reflectance, or Haze
2. Aperture size (6mm, 10mm, 17mm, or 22/25mm)
3. Specular included or excluded condition (SCI or SCE)
4. UV included or excluded condition

Reflectance Calibration Procedure

To calibrate your spectrophotometer in Reflectance Measurement Mode you need to use your application software. Follow these steps:

1. Launch the calibration process from the software interface.
2. You will be prompted to present and then remove the calibration tile and to prepare for the black trap.
3. Once the calibration process is complete, the Calibrated LED becomes lit. Any change to the spectrophotometer configuration may result in the calibration LED turning from green (calibrated) to red (not calibrated). Remember that each configuration needs to be calibrated.

Transmission Calibration Procedure

To calibrate your spectrophotometer in Transmission Measurement Mode you need to first locate the following items in your transmission kit box:

Barium Coated Aperture Plate

Transmission Sample Holder

Black Plastic Blocking Panel

1. Using your application software launch the calibration process from the software interface.
2. Mount the Barium Coated Aperture plate to the measurement port at the front of the instrument. Follow any prompts from the software regarding the white calibration.
3. When you are prompted for the Black Calibration, place the Sample Transmission Holder inside the Transmission compartment and load the Black Plastic Blocking Panel in the Transmission sample holder. For more information on loading the Sample Transmission Holder in the Ci7, refer to Taking Transmission Measurements on page 13.
4. Click OK to any message for black trap calibration.

5. Once the calibration process is complete, the Calibrated LED becomes lit. Any change to the spectrophotometer configuration may result in the calibration LED turning from green (calibrated) to red (not calibrated). Remember that each configuration needs to be calibrated.

Taking Reflectance Measurements

To take a measurement using your spectrophotometer, follow these steps to ensure an accurate reading.

1. Prepare your sample for measurement.
 2. Open the sample arm on the spectrophotometer to the fully open position. Present the sample at the view port and slowly close the sample arm. The spring on the sample arm is dampened to prevent the arm from closing with too much force and possibly damaging the sample.
 3. Use the preview monitor, your computer screen, or the drop down door to view the sample and adjust the sample measurement targeting area.
 4. Trigger the measurement using one of the following methods:
 - a. Select "Measure Standard" or "Measure Trial" from your application software interface. Follow the software instructions for loading the sample at the view port.
- OR**
- b. Press the Standard or Trial button on the Color i7 Status Panel.
5. The measurement is taken. The data are presented to you in your application software. Follow the instructions for saving the data in the software.

Taking Transmission Measurements

An optional accessory for the Color i7 spectrophotometer is the Transmission Kit. You will need this kit in order to take transmission measurements. Please refer to Optional Accessories on page 5 for more information on the Transmission kit.

Before taking a transmission measurement...

1. Set the Color i7 to Transmission Mode using your application software.
2. Mount the Barium Coated Aperture plate to the measurement port at the front of the instrument.
3. Make sure the instrument is calibrated for the measurement mode.

You will notice the Transmission LED is lit on the Status Panel based on your selection in the software. The Color i7 transmission sample holder is designed to mount inside the transmission compartment. It is used to measure thin films at both the sphere (total transmission) and at the lens (direct transmission). Each transmission kit contains five sample holders: small (6 mm), medium (10 mm), 17 mm, large (22 mm), and a cuvette sample holder (for measuring liquids). Choose the sample holder appropriate for your application. *Note: Liquids are measured using the cuvette sample holder.*

To take a transmission measurement, proceed as follows.

1. Remove the Transmission Cover Fixing Screw on the side of the Ci7. Set it aside.




Figure 5. Spectrophotometer with Transmission Cover Partially Open

- Open the spectrophotometer transmission cover. Apply pressure with your fingertips to each side of the cover and gently push the cover to the rear of the spectrophotometer. The cover opens and closes in a telescoping fashion. The spectrophotometer interior should be exposed.




Figure 6. Transmission Holder at the Sphere (Total Measurement)




Figure 7. Transmission Holder at the Lens (Direct Measurement)

- Align the sample holder base plate pins to the base plate mounting channel holes inside the transmission area. There are mounting holes in the channel at both the sphere and the lens. Be sure to mount the sample holder at the sphere for a total transmission measurement or at the lens for a direct transmission measurement.
- Attach the sample holder to the base plate with the mounting screws. The above picture shows the cuvette holder mounted at the sphere. To mount the small or medium sample holder, position the appropriate stops and springs (medium stop, medium spring, etc.) over the opening in the sphere.
- Use sample holder pull tab to pull back the sample holder towards you. Mount your sample in the sample holder.
- Position the Spectralon plaque at the viewport.

7. Trigger the measurement using one of the following methods:
 - a. Select "Measure Standard" or "Measure Trial" from your application software. Follow the software instructions for loading the sample at the view port.

OR

- b. Press the Standard or Trial button on the Color i7 Status Panel.
8. The measurement is taken. The data are presented to you in your application software. Follow the instructions for saving the data in the software.

Taking Haze Measurements

To take a Haze measurement you will usually be required to calibrate for the haze measurement first, then you will take the actual haze measurement. The only exception to this is if you were already in Haze Measurement mode using a *current* haze calibration. The calibration is not launched.

Follow these steps:

1. Mount the LAV aperture plate at the measurement port.
2. Select “Haze” as the measurement type within your software interface.
3. Haze Calibration is automatically launched. Follow the prompts from the software regarding loading the spectralon plaque and the black trap.
4. Once the Haze Calibration is complete you may begin to take Haze measurements.
5. Load your sample in the Transmission sample holder within the Transmission compartment.
6. Select “Measure Standard”, “Measure Trial”, or press the appropriate measure button on the Ci7.
7. Follow the prompts from the software regarding loading the spectralon plaque and the black trap.
8. If you later change the Measurement Mode to another measurement type than Haze you will be prompted to calibrate the Ci7.

UV Control

Your spectrophotometer is equipped with an automated 400nm UV filter. This can be set to fully **Exclude** the UV portion of the light source in the spectrophotometer or can be used to calibrate and adjust the UV level, for instance to match the UV component of **D65** daylight. The Color i7 supports 3 pre-selected UV calibration positions for the filter you may wish to calibrate to D65 or other levels of UV. A UV illuminant checker is provided that has been calibrated with a CIE whiteness value for true D65. Your application software will drive the UV calibrator making successive measurements until it finds the correct calibrator position to give this value.

Aperture Control

To change the aperture setting on the spectrophotometer you need to use your application software and the Aperture Plates. Select an aperture setting of SAV (6mm), MAV (10mm), 17 mm, or LAV (25mm).

Note: If you select an option in your application software to *automatically* configure the zoom lens position (lens = port), the spectrophotometer automatically moves the zoom lens whenever you change the aperture plate.

If you prefer to not have matching Area of View and Zoom Lens setting (to have a different illumination setup), do not have your application software automatically configure the lens position (lens = port). Instead, choose an alternate Lens setting such as MAV or LAV. Keep in mind that if the zoom position and the installed aperture plate do not match, the Aperture LED will blink to indicate this discrepancy.

To install an aperture plate on the Color i7, proceed as follows.




Figure 8. Mounting the Aperture Plate on the Spectrophotometer

1. Prepare the aperture plate to be installed and make sure it is nearby.
2. Open the sample arm to the fully open position
3. Open the sample preview door. Apply pressure at the back of the plate if necessary to remove it.
4. Locate the plate to be installed and fit the aperture over the rim on the spectrophotometer. Press the new plate firmly into place. The plate is magnetized to prevent it from falling out.
5. Gently close the sample arm.

Specular Control

To change the Specular Component setting on the spectrophotometer you need to use your application software. Select the desired Specular Component Setting- Included (SCI), Excluded (SCE), or Dual Mode

(SCE/SCI). Be sure to save the setting. You will notice the LED for either setting (or both if you have dual mode) becomes lit based on your selection. The Color i7 simultaneously measures Specular included and Specular excluded for all reflectance measurements. Your application software should decide which measurement data to request from the spectrophotometer according to the user requirements.

Maintaining Your Spectrophotometer

Cleaning the Calibration Tiles

Ceramic standards (calibration tiles) are widely used in color science as standards of reflectance factor. Their principal virtue is the stability of their reflection properties. If they are to serve their intended purpose, it is necessary that the surfaces of these tiles be maintained in a stable condition. The cleaning of any precision optic risks degrading the surface. Therefore, the need for cleaning should be minimized by returning the tile to its storage case or covering it with a protective bag when it is not in use. If cleaning is required, the following procedure is recommended.

Materials Required

Camel's-Hair Brush: Available at most camera, hardware, or art supply stores.

Dust free tissue: Use a lens tissue, which meets Federal Specification NNN-P-40A, Type I or equivalent.

To remove dust, lint, and invisible gritty particles, proceed as follows:

1. Lint and other small particles are usually best observed by illuminating the tile with a diffuse light sources at an angle so that the light does not produce surface glare. Inspect the tile at an angle rather than looking directly at the tile's front surface.
2. Brush the tile's surface with a camel's-hair brush.
3. Breathe a light mist of condensed vapor at the center of the tile.
4. Immediately wipe the tile's surface *lightly* with lens tissue. Avoid smearing the tile with natural greases and perspiration from the hands by wiping with the untouched center part of the lens tissue.

Cleaning the Black Plastic Blocking Panel

Dust on the black plastic blocking panel can be very tightly bound by static electricity. To remove the dust, blow canned air across the opening.

Color Science Training

X-Rite offers color management training programs to suite your needs. We also offer a variety of workshop programs at our facilities or we can come to you. The more training you have regarding color science, your instrument, and your color science software, the more optimum your color environment. For more information please visit our website <http://www.gretagmacbeth.com/index/events/events-training.htm> or call 1 888-439-4403 x 219 for assistance from a Training Coordinator.

Personal Color Trainer Live Remote Training

- Personal Color Trainer is a live one-on-one remote training session with a color expert to discuss the topics for your choice. The 55 minutes you receive with your Personal Color Trainer is custom fit around your industry, equipment and needs with live video and remote desktop sharing. Please visit our website www.personalcolortrainer.com or call 888-439-4403 x 219 for assistance from a Training Coordinator

Introduction to Color IQC and Consulting for Color Management

- These two-hour Webex seminars provide an instruction for new users and cover advanced features for experienced users of Color IQC software.

Introduction to Color Measurement

- This two-hour Webex seminar provides a brief introduction to color measurement for industrial applications

On-Site Training and Consulting for Color Management

- If your training needs are specific to your workflow, do you have several staff members to train or you cannot interrupt production to send your staff to off-site training, have our training experts come to you.

Fundamentals of Color and Appearance Seminar

- This traveling seminar is designed for anyone involved in evaluating color and appearance of physical materials, including paints, plastics, textiles, and more. This seminar will introduce you to the basic concepts of color and appearance science and assist you in identifying the variables, which contribute to color variation in your process. You will learn instrumentation, visual and instrumental quality control, and color data communication. Please check <http://www.gretagmacbeth.com/index/events/events-training.htm> for dates and locations.

Fundamentals of Color and Appearance Reference Book

- The Fundamentals of Color and Appearance is the definitive reference book on color theory and application. You do not have to be a color expert to understand complex color concepts. This book is part of the Fundamentals of Color Course but can be purchased through The GretagMacbeth e shop found at www.gretagmacbeth.com. The book contains dozens of practical and easy-to-follow tips and techniques to help you improve color matching. Also included is a handy outline to help you develop your own color control program.

Technical Service

In the event that you are unable to solve a problem, you may contact our Technical Service Department.



Corporate Headquarters - USA

4300 44th Street SE
Grand Rapids, Michigan 49512
Phone 1 800 248 9748 or 1 616 803 2100
Fax 1 800 292 4437 or 1 616 803 2705

Corporate Headquarters - Europe

Althardstrasse 70
8105 Regensdorf
Switzerland
Phone (+41) 44 842 24 00
Fax (+41) 44 842 22 22

Corporate Headquarters - Asia

Room 808-810
Kornhill Metro Tower, 1 Kornhill Road
Quarry Bay, Hong Kong
Phone (+852) 2 568 6283
Fax (+852) 2 885 8610

Please visit www.xrite.com for a local office near you.

Spare Parts and Accessories

The Color i7 Spectrophotometer has optional accessories that you may order by calling the Customer Service Department in the US at 1-800-248-9748. The following accessories are available:

Transmission kit: this kit includes a calibration standard, a transmission cuvette/ thin films sample holder, a transmission cuvette and a handy storage case.	A-TJ/I7
LCD Video Preview Monitor	A-VPM/I57LCD
Toggle Pad Subassembly with White Ceramic Backing: User-installable replacement toggle pad that includes an embedded white ceramic backing.	GM29021020
Stand for Horizontal Measurement Plane	A-MAV57
MCS Calibrated Disposable Standards (13 /2"x2" Tiles) including one calibration (for use with NetProfiler)	368237
MCS Calibrated BCRA Standards [13 / 1.25" Tiles] (for use with NetProfiler)	369604

Index

Aperture Control	16	Photometric range	3
Black Plastic Blocking Panel	17	Preview button	10
Buttons	10	Preview Method	
Calibration.....	11	Computer Monitor.....	8
Cleaning	17	Preview Monitor	8
Color Science Information.....	18	Installation.....	8
Company Addresses.....	19	Reflectance	
Computer Monitor Used for Sample Preview	8	Calibration.....	11
Getting Help.....	19	Measurements.....	12
Haze Measurements	15	Repeatability	3
Hinged Sample Door.....	7	Safety	2
Installation.....	1, 6	Spare Parts and Accessories.....	20
Inter-Instrument Agreement.....	3	Specifications.....	3
LCD Sample Preview Monitor	8	Environmental	3
Maintaining Your Spectrophotometer	17	Spectral Range	3
Measurement time.....	3	Specular Control	16
Operation.....	10	Standard and Trial buttons	10
Optional Accessories	5	Status panel	10
Optional Color i7 Sample Preview Monitor ...	8	Technical Service.....	19
Parts.....	20	Training.....	18
Performance Specifications	3	Transmission	
		Calibration.....	11
		kit.....	5
		Measurements.....	13
		Unpacking.....	4
		UV Control.....	15

